Arduina IIna

Arddino ono
Autor: Data de publicació: 03-08-20
SainSmart UNO R3 Board A
Overview
The Sainsmart Uno R3 is a constant of the Sainsmart Uno R3 is a consta

014

ATmega328P ATmega16U2 Compatible For Arduino

microcontroller board based on the ATmega328. It has 14 digital input/output pins (of which outs), 6 analog inputs, a 16 MHz ceramic resonator, a USB connection, a power jack, an utton. It contains everything needed to support the microcontroller; simply connect it to a or power it with a AC-to-DC adapter or battery to get started.

Revision 3 of the board has the following new features:

1.0 pinout: added SDA and SCL pins that are near to the AREF pin and two other new pins placed near to the RESET pin, the IOREF that allow the shields to adapt to the voltage provided from the board. In future, shields will be compatible with both the board that uses the AVR, which operates with 5V and with the Sainsmart Due that operates with 3.3V. The second one is a not connected pin, that is reserved for future purposes. Stronger RESET circuit.

Atmega 16U2 replace the 8U2.

Note: Click The Picture for the different UNO R3

Sainsmart Uno R3 2012

Sainsmart Uno R3 2013

ATmega328

MEGA328P-AU	
5V	
3.3V-5V (Switch)	
7-12V	
7-12V	
6-20V	
6-20V	
14 (of which 6 provide PWM output)	
14 (of which 6 provide PWM output)	
6	
8 (Add A6/A7 port)	
40 mA	

40 mA	
50 mA	
50 mA	
32 KB (ATmega328) of which 0.5 KB used by bootloader	
32 KB (ATmega328) of which 0.5 KB used by bootloader	
oz NB (Nimegaozo) di wildir olo NB asca by sociloadei	
2 KB (ATmega328)	
2 KB (ATmega328)	
1 KB (ATmega328)	
1 KB (ATmega328)	
16 MHz	
16 MHz	